

 **PHOENIX GOLD**

**ZX**  
series  
HIGH  
PERFORMANCE



# **ZX-SERIES COAXIAL SPEAKERS**

ZX5CXS

## ZX-SERIES - COXIAL SPEAKERS

SPECIFICATION	ZX5CX5
Speaker Type	2-Way Coaxial
Speaker Size	5.25"(130mm)
Impedance	4Ω
Frequency Response	100Hz-20KHz
Power Handling (RMS)	60W
Power Handling (MAX)	180W
Sensitivity	87dB
Re	3.6Ω
Fs	100Hz
Qms	4.869
Qes	1.359
Qts	1.062
Cms	578.125uM/N
Vas	7.414L
BL	2.882Tm
Sd	95.03cm <sup>2</sup>
Mms:	5.878g
EBP:	63
Mounting Depth:	55mm
Mounting Diameter:	120mm
Outer Diameter:	130mm
Speaker Grills:	Yes
Unit:	Pair

### INSTALLATION

To ensure proper installation, check that the speakers fit into your desired location - this could require removal of existing vehicle speakers. Check the surrounding area before drilling or cutting holes. DO NOT work near fuel tanks, fuel lines hydraulic lines or electrical wiring. Once installed make sure the speaker is firmly fixed in your vehicle.

Always ensure that the speaker and cables are securely attached and installed in such a way that no cables can be pinched or damaged. Phoenix Gold accepts no responsibility for damage or injury in relation to inappropriate installation of this product.

#### Disclaimer

Ensure your safety and the well-being of those around you by following these essential guidelines:

- Keep all product materials and packaging away from children, pets, or anyone at risk of suffocation.
- Exposure to noise levels above 85 dB can cause permanent hearing damage.
- Extreme sound frequencies reduce perception abilities that are essential in road traffic conditions; do not let loud volumes distract from being mindful behind the wheel.
- Phoenix Gold takes no responsibility for any physical harm or damage caused by improper use of their products.
- Ensure that all metals and raw materials are disposed of in accordance with local regulations and environmental standards to minimise any negative impact on the environment.

#### Warranty

Phoenix Gold products come with a limited warranty and are covered by our regional distribution partners and their terms and conditions. You can find out more information by contacting your local retailer or distributor.